

Constants: $e = 1.6 \times 10^{-19} \text{ C}$ $m_p = 1.67 \times 10^{-27} \text{ kg}$ $m_e = 9.1 \times 10^{-31} \text{ kg}$ $c = 3 \times 10^8 \text{ m/s}$ $\text{micro} = 10^{-6}$
 $\epsilon_o = 8.85 \times 10^{-12} \text{ C}^2/\text{N} \cdot \text{m}^2$ $k = 1/(4\pi\epsilon_o) = 9 \times 10^9 \text{ N} \cdot \text{m}^2/\text{C}^2$ $\mu_o = 4\pi \times 10^{-7} \text{ T} \cdot \text{m/A}$ $\text{nano} = 10^{-9}$

Coulomb's Law: $|\vec{F}| = \frac{|q_1||q_2|}{4\pi\epsilon_o r^2}$ (point charge)

Electric field: $\vec{E} = \frac{\vec{F}}{q}$ $\vec{E} = \frac{q}{4\pi\epsilon_o r^2} \hat{r}$ (point charge) $\vec{E} = \int \frac{dq}{4\pi\epsilon_o r^2} \hat{r}$ (general) $E = \frac{\sigma}{2\epsilon_o}$ (plane)

Gauss' law: $\Phi = \hat{n} \cdot \vec{E} A = \oint \hat{n} \cdot \vec{E} dA = \frac{q_{enc}}{\epsilon_o}$

Energy: $W = \int \vec{F} \cdot d\vec{s} = \frac{1}{2}mv_f^2 - \frac{1}{2}mv_i^2 = K_f - K_i$

For conservative forces $U_f - U_i = - \int \vec{F} \cdot d\vec{s} \rightarrow K_i + U_i = K_f + U_f$

Electric potential: $V = \frac{U}{q}$ $V = \frac{q}{4\pi\epsilon_o r}$ (point charge) $V = \int \frac{dq}{4\pi\epsilon_o r}$ (general)

$V_b - V_a = - \int_a^b E_x dx = - \int_a^b \vec{E} \cdot d\vec{s}$ $E_x = -\frac{\partial V}{\partial x}$, $E_y = -\frac{\partial V}{\partial y}$, $E_z = -\frac{\partial V}{\partial z}$

Capacitors: $q = CV$ $C = \frac{K\epsilon_o A}{d}$ (parallel-plate) $C = C_1 + C_2$ (parallel)

$$U = \frac{q^2}{2C} \quad u = \frac{1}{2}\epsilon_o E^2 \quad \frac{1}{C} = \frac{1}{C_1} + \frac{1}{C_2} \text{ (series)}$$

Resistors: $i = \frac{dq}{dt} = jA$ $R = \frac{V}{i}$ $R = \frac{\rho L}{A}$ (wire) $P = iV$ $R = R_1 + R_2$ (series)

$q = CV(1 - e^{-t/RC})$ (charging) $q = q_o e^{-t/RC}$ (discharging) $\frac{1}{R} = \frac{1}{R_1} + \frac{1}{R_2}$ (parallel)

Magnetism: $\vec{F} = q\vec{v} \times \vec{B}$ $\vec{F} = i\vec{L} \times \vec{B}$ $\mu = NiA$ $\vec{\tau} = \vec{\mu} \times \vec{B}$ $U = -\vec{\mu} \cdot \vec{B}$

$d\vec{B} = \frac{\mu_o i d\vec{s} \times \hat{r}}{4\pi r^2}$ $\oint \vec{B} \cdot d\vec{s} = \mu_o i_{enc}$ $B = \frac{\mu_o i}{2\pi R}$, (wire) $\frac{\mu_o i}{2R}$ (loop center), $\frac{\mu_o i N}{L}$ (solenoid)

Induction: $\Phi_B = \hat{n} \cdot \vec{B} A = \oint \hat{n} \cdot \vec{B} dA$ $\mathcal{E} = \oint \vec{E} \cdot d\vec{s} = -\frac{d\Phi_B}{dt}$

$L = N\Phi_B/i$ (definition) $L = \mu_o n^2 Al$ (solenoid) $\mathcal{E} = -L\frac{di}{dt}$ $\mathcal{E}_1 = -M\frac{di_2}{dt}$ $L = L_1 + L_2$ (series)

$U_B = \frac{1}{2}Li^2$ $u_B = \frac{B^2}{2\mu_o}$ $i = i_o e^{-t/\tau_L}$ $\tau_L = L/R$ $\frac{V_s}{V_p} = \frac{N_s}{N_p}$ $\frac{1}{L} = \frac{1}{L_1} + \frac{1}{L_2}$ (parallel)

AC Circuits: $\omega = \frac{1}{\sqrt{LC}}$ (LC circuit) $\mathcal{E} = \mathcal{E}_m \sin(\omega t)$ $i = I \sin(\omega t - \phi)$ (driven RLC) $P_{avg} = \frac{1}{2}I\mathcal{E}_m \cos \phi$

$\tan \phi = \frac{X_L - X_C}{R}$ $I = \frac{\mathcal{E}_m}{Z}$ $Z = \sqrt{R^2 + (X_L - X_C)^2}$ $X_L = \omega L$, $X_C = \frac{1}{\omega C}$, $v_L = L\frac{di}{dt}$, $v_C = \frac{q}{C}$

$q = Q_o e^{-Rt/(2L)} \cos(\omega't + \phi)$ $\omega' = (\omega^2 - (R/(2L))^2)^{1/2}$

Last 2 Maxwell's Eqs.: $\oint \vec{B} \cdot \hat{n} dA = 0$ $\oint \vec{B} \cdot d\vec{s} = \mu_o \epsilon_o \frac{d\Phi_E}{dt} + \mu_o i_{enc}$ $i_d = \epsilon_o \frac{d\Phi_E}{dt}$

$$\mathbf{EM\ Waves:} \quad c = \frac{E}{B} = \frac{1}{\sqrt{\mu_0 \epsilon_0}} \quad \vec{S} = \frac{1}{\mu_0} \vec{E} \times \vec{B} \quad I = S_{avg} = \frac{1}{c\mu_0} E_{rms}^2 \quad E_{rms} = \frac{E_m}{\sqrt{2}} \quad I = \frac{P_s}{4\pi r^2}$$

$$I = I_o \cos^2 \theta \quad n_1 \sin \theta_1 = n_2 \sin \theta_2 \quad \theta_c = \sin^{-1} \frac{n_2}{n_1} \quad \theta_B = \tan^{-1} \frac{n_2}{n_1} \quad p_r = \frac{I}{c} \text{ (absorp.)}, \frac{2I}{c} \text{ (refl.)}$$

$$\vec{E} = \vec{E}_m \sin(\vec{k} \cdot \vec{r} - \omega t) \quad \vec{B} = \vec{B}_m \sin(\vec{k} \cdot \vec{r} - \omega t) \quad \vec{E}_m \perp \vec{B}_m \perp \vec{k} \quad c = \omega/k = f\lambda$$